

Filed by Express Mail
(Receipt No. HS236585)
on 12/13/00
pursuant to 37 C.F.R. 1.10.
by Shenalee Z.

SPECIFICATION

TO ALL WHOM IT MAY CONCERN:

BE IT KNOWN THAT I, Kazunori Horachi, a citizen of Japan residing at Kawasaki, Japan have invented certain new and useful improvements in

APPARATUS FOR TRANSMISSION BETWEEN SUBSCRIBER
TERMINALS AND ANY TYPES OF SWITCHES

of which the following is a specification : -

TITLE OF THE INVENTION

APPARATUS FOR TRANSMISSION BETWEEN
SUBSCRIBER TERMINALS AND ANY TYPES OF SWITCHES

5 BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention generally relates to subscriber-system transmission apparatuses, and particularly relates to a subscriber-system
10 transmission apparatus which is equipped with interface connectable to any types of switches of the IDLC type or the UDLc type and connectable to various switches of different vendors.

2. Description of the Related Art

15 Fig.15 is an illustrative drawing showing a remote-station switch system having a UDLc (universal digital loop carrier) network configuration. Fig.16 is an illustrative drawing showing a remote-station switch system having an
20 IDLC (integrated digital loop carrier) network configuration.

The remote-station switch system of Fig.15 having a UDLc network configuration is of a type that is used together with an analog switch. A
25 subscriber-system transmission apparatus 1 shown in Fig.15, which serves as a remote terminal RT, covers subscriber terminals that are scattered around in remote areas (CSA: carrier service areas) far away from an analog switch 4. The subscriber-system
30 transmission apparatus 1 connects these subscriber terminals to the analog switch 4 via optical-fiber transmission lines. In one example of the UDLc network configuration, the subscriber-system transmission apparatus 1 is connected to the analog
35 switch 4 via an optical-fiber transmission line, an optical transmission apparatus 9 having optical-signal multiplexing/demultiplexing functions, and a

transmission apparatus 8 having electrical-signal multiplexing/demultiplexing functions. In another example of the UDLC network configuration, the subscriber-system transmission apparatus 1 is
5 connected to the analog switch 4 via an optical-fiber transmission line and a center-station-system (COT) transmission apparatus 5 having optical-signal multiplexing/demultiplexing functions.

The remote-station switch system of Fig.16
10 having an IDLC network configuration is of a type that is used together with a digital switch. In one example of this configuration, the subscriber-system transmission apparatus 1 is connected to a digital switch 3 of a TR08 type via an optical-fiber
15 transmission line and the optical transmission apparatus 9 having optical-signal multiplexing/demultiplexing functions. In another example of this configuration, the subscriber-system transmission apparatus 1 is connected to a digital
20 switch of a TR303 type via an optical-fiber transmission line and the optical transmission apparatus 9. The former example corresponds to a scheme in which signaling is incorporated into subscriber lines when it is transmitted, and the
25 latter example corresponds to a scheme in which signaling is transmitted via another path. In either example of the IDLC network configuration, the transmission apparatus 8 having electrical-signal multiplexing/demultiplexing functions is made
30 obsolete while it is of necessity in the UDLC network configuration.

The subscriber-system transmission apparatus 1 that is connected to the analog switch 4 or the digital switch 2 or 3 covers ISDN subscriber
35 terminals. In what follows, a description will be given of an ISDN multiplexing scheme.

ISDN MULTIPLEXING SCHEME

At a U point on a digital subscriber line, signals corresponding to the following items are provided.

- 5 - 64 kbps B1 and B2 channels (data channel)
- 16 kbps D channel (data channel)
- synchronization word
- M channel (for maintenance purpose)
 - 1. crc (cyclic redundancy check) bit
- 10 2. febe (far end block error) bit
- 3. eoc (embedded operation channel) bit
- 4. I (indicator) bit

Fig.17 shows a related-art UDLC system.

- 15 In the related-art UDLC system as shown in Fig.17, 2B+D signals and M-channel signal are multiplexed as they are received through a U point (i.e., an interface between a switch and a COT), followed by transmitting the multiplexed signals to
- 20 the subscriber-system transmission apparatus 1 situated on the remote station side. The subscriber-system transmission apparatus 1 demultiplexes the received signals, and transmits the demultiplexed signals to a U point (i.e., an
- 25 interface between a remote station RT and an NT1 apparatus 6). The same operation is performed when signals are transmitted in the opposite direction.

- The signals described above are multiplexed by the unit of DS0 (64 kbps) on digital
- 30 facility. Multiplexing schemes used in this operation include:

- 1) 3DS0 time division multiplexing; and
- 2) 4:1 time division multiplexing.

35 3DSO TIME-DIVISION-MULTIPLEXING SCHEME

The 3DSO time-division-multiplexing scheme uses 3 DS0s for the purpose of multiplexing 2B+D on

a digital subscriber line into one set of signals.
Allocation of DS0s is as follows.

B1 channel --- DS0 (B1)

B2 channel --- DS0 (B2)

5 D channel, M channel --- DS0 (D+)

DS0 (B1), DS0(B2), and DS0(D+) as described above
together constitute 3DS0.

DS0 that is allocated to the D channel and
the M channel is called a D+ byte. The related-art
10 ISDN switches employ 3DS0 time-division-multiplexing
scheme, and three DS0 time slots are allocated on
the digital facility at all times.

4:1 TIME-DIVISION-MULTIPLEXING SCHEME

15 In the 4:1 time-division-multiplexing
scheme, the B1 and B2 channels are allocated to 2
DS0s, and four D channels are allocated to one DS0
for the purpose of multiplexing 2B+D on the digital
subscriber line into one set of signals. Allocation
20 of DS0s is as follows.

B1 channel --- DS0

B2 channel --- DS0

D channel --- DS0

(own DSL : 2 bits such as bits 0 and 1)

25 D channel --- same as above
(other DSL : 2 bits such as bits 2 and 3)

D channel --- same as above

(other DSL : 2 bits such as bits 4 and 5)

D channel --- same as above

30 (other DSL : 2 bits such as bits 6 and 7)

M channel (eoc + I bit) --- EOC path

(eoc: embedded operation channel, I: indicator)

In the 4:1 time-division-multiplexing
35 scheme, four D channels exclusively occupies the
whole DS0. Because of this, it is necessary to
attend to message conversion between EOC/eoc and

EOC/Ibit on the ISDN-channel card with respect to M-channel information for maintenance purposes, so that the information is transmitted to the switch through an EOC path serving as a maintenance channel for the transmission device, i.e., through a control path between the switch and the subscriber-system transmission apparatus.

In the 3DS0 time-division-multiplexing scheme that is typically used in the analog-switch system or in the TR08-type digital-switch system, one DS0 is allocated to one D channel of the ISDN. For the purpose of efficient use of transmission lines, however, it has been required in an increasing number of cases to use the 4:1 time-division-multiplexing scheme in which one DS0 is allocated to four D channels. In the TR303-type digital switch system that has been recently chosen more often than not, the 4:1 time-division-multiplexing scheme is in prevalent use.

The 4:1 time-division-multiplexing scheme multiplexes four D channels, and transmits them as one DS0. While the conventional 3DS0 time-division-multiplexing scheme transmits the M channel as the D+ byte, the 4:1 time-division-multiplexing scheme cannot use the DS0 space for this purpose. As a result, it becomes necessary to convert the eoc bit and the I (indicator) bit of the M channel into EOC (i.e., the control path between the switch and the subscriber-system transmission apparatus) so as to attend to transmission between the switch and the subscriber-system transmission apparatus by using the EOC path that is separate from DS0.

If a new interface is newly designed for the EOC path, compatibility with conventional channel cards would be lost. A further problem is that there is a need to reconstruct the entire configuration of apparatus in response to the

creation of new interface.

Switches that support the TR303-type digital switches are currently manufactured by various manufacturers. In order to connect with the TR303-type digital switches of various manufactures, alarm information on the ISDN subscriber lines needs to be transmitted by using a method of notification that complies to the different requirements of switches of different manufactures. Because of this, the subscriber-system transmission apparatus needs to manage and control alarm information on the subscriber line and to transmit the information through the control path (i.e., EOC) between the switch and the subscriber-system transmission apparatus.

The TR303-digital-switch system as described above employs the 4:1 time-division-multiplexing mode function for the purpose of connecting with IDTs (integrated digital terminals). In the 4:1 time-division-multiplexing mode, the EOC (embedded operation channel) is used to exchange control information between the TR303-type switch and the subscriber-system transmission apparatus 1 of the remote station. The standard TR-397 concerning the ISDN does not set forth details of the EOC (i.e., standards of alarm notification for the ISDN subscribers) in the 4:1 time-division-multiplexing mode. Manufactures that make switches supporting the TR303-type switches design and produce switches based on their own ISDN alarm-detection specifications. The subscriber-system transmission apparatuses also need to be changed in terms of their design specifications in compliance to the requirements of manufacturers. This gives rise to a problem of lack of universal applicability.

Accordingly, there is a need for a subscriber-system transmission apparatus which is

adaptable to either type of ISDN switches that is based on the 3DS0 time-division-multiplexing scheme or the 4:1 time-division-multiplexing scheme while keeping compatibility with the prior-art
5 multiplexing/demultiplexing interface.

SUMMARY OF THE INVENTION

It is a general object of the present invention to provide an apparatus that substantially
10 obviates one or more of the problems caused by the limitations and disadvantages of the related art.

Features and advantages of the present invention will be set forth in the description which follows, and in part will become apparent from the
15 description and the accompanying drawings, or may be learned by practice of the invention according to the teachings provided in the description. Objects as well as other features and advantages of the present invention will be realized and attained by
20 the apparatus particularly pointed out in the specification in such full, clear, concise, and exact terms as to enable a person having ordinary skill in the art to practice the invention.

To achieve these and other advantages and
25 in accordance with the purpose of the invention, as embodied and broadly described herein, the invention provides an apparatus for transmission between subscriber terminals and digital switches that employ a 4:1 time-division-multiplexing scheme, the
30 apparatus including a main path for carrying signals between the subscriber terminals and digital switches, a control path which is separate from said main path and carries control information for maintenance purpose, and an interface-&-control unit
35 which converts the control information so as to conform to specifications of the said digital switches wherein the conversion of the control

information is based on switch settings made to said interface-&-control unit.

In the above apparatus, the switch settings are selected in accordance with the types of the digital switches, and are used to conform to the specifications of the digital switches. This ensures that the apparatus can cope with various types of digital switches, providing universal applicability in terms of connections with digital switches.

Further, according to another aspect of the present invention, an apparatus for transmission between subscriber terminals and digital switches that employ a 4:1 time-division-multiplexing scheme includes a main path for carrying signals between the subscriber terminals and digital switches, a control path which is separate from said main path and carries control information for maintenance purpose, and a subscriber-side interface unit which transmits an alarm notification to the digital switches via said control path wherein the alarm notification conforms to specifications of said digital switches based on switch settings made to said subscriber-side interface unit.

In the apparatus as described above, the switch settings are selected in accordance with the types of the digital switches used in the network to which subscriber terminals belong, and are used to conform to the specifications of the digital switches. This ensures that the apparatus can cope with the various types of digital switches used in the network regardless of the network to which the subscribers belong. In other words, any user using any network can be covered by the apparatus of the present invention.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig.1 is a block diagram of an IDLC system including a subscriber-system transmission apparatus according to an embodiment of the present invention;

Fig.2 is a block diagram of a relevant
5 portion of the subscriber-system transmission apparatus for the purpose of explaining an EOC path during a 4:1 time-division-multiplexing mode;

Fig.3 is a block diagram showing details
10 of a portion relevant to settings of switch options in the subscriber-system transmission apparatus;

Fig.4 is a block diagram showing a configuration of a U-point-termination unit;

Fig.5 is a table showing ISDN-alarm-notification commands and values thereof that are
15 transmitted in response to the switch option settings corresponding to each switch vendor;

Fig.6 is a table showing ISDN-alarm-notification commands and values thereof that are
20 transmitted in response to the switch option settings corresponding to each switch vendor;

Fig.7 is a table showing ISDN-alarm-notification commands and values thereof that are
transmitted in response to the switch option settings corresponding to each switch vendor;

Fig.8 is a table showing ISDN alarm
25 notification commands and values thereof transmitted in response to switch settings of an EOC-control unit of an EOC control card;

Fig.9 is a table showing ISDN alarm
30 notification commands and values thereof transmitted in response to switch settings of the EOC-control unit of the EOC control card;

Fig.10 is a table showing ISDN alarm
notification commands and values thereof transmitted
35 in response to switch settings of the EOC-control unit of the EOC control card;

Fig.11 is a table showing ISDN alarm

notification commands and values thereof transmitted in response to switch settings of the EOC-control unit of the EOC control card;

Fig.12 is a table showing standards of
5 ISDN alarm messages that are transmitted in response to switch settings of the SW-interface unit of the SW-interface unit;

Fig.13 is a table showing standards of
10 ISDN alarm messages that are transmitted in response to switch settings of the SW-interface unit of the SW-interface unit;

Fig.14 is a table showing standards of
15 ISDN alarm messages that are transmitted in response to switch settings of the SW-interface unit of the SW-interface unit;

Fig.15 is an illustrative drawing showing a remote-station switch system having a UDLC network configuration;

Fig.16 is an illustrative drawing showing
20 a remote-station switch system having an IDLC network configuration; and

Fig.17 shows a related-art UDLC system.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

25 In the following, embodiments of the present invention will be described with reference to the accompanying drawings.

Fig.1 is a block diagram of an IDLC system including a subscriber-system transmission apparatus
30 according to an embodiment of the present invention.

In Fig.1, the subscriber-system transmission apparatus 1 is connected to TR303-type digital switches 2A, 2B, and 2C corresponding to respective vendors A, B, and C. This connection is
35 established via optical-fiber transmission lines based on DS1 interface. Further, the subscriber-system transmission apparatus 1 is connected to

analog switches 4a, 4b, and 4c corresponding to respective vendors a, b, and c via optical-fiber transmission lines and a center-station-system transmission apparatus 5.

5 The subscriber-system transmission apparatus 1 covers a plurality of ISDN subscriber terminals 7 via NT1 (network-terminal-apparatus-1) apparatuses 6. Each user of the subscriber
10 provider network where service-provider networks adopt switches manufactured by vendors of their own choice. When a user attempts to transmit or receive a call, he/she establishes connection with the service-provider network to which he/she belongs.

15 A control console 10 connected to the subscriber-system transmission apparatus 1 is comprised of a personal computer or the like, which is used for making various settings to the subscriber-system transmission apparatus 1 in terms
20 of switch options and the like.

 In this manner, the subscriber-system transmission apparatus 1 is provided with the DS1 interface for the IDTs (integrated digital terminals), and includes an EOC interface unit and a
25 cross-connect unit therein for switching between the 3DS0 time-division-multiplexing scheme and the 4:1 time-division-multiplexing scheme. This makes it possible to assume an IDLC configuration based on the 4:1 time-division-multiplexing scheme. Further,
30 this system can be regarded as the 3DS0-scheme system having an additional configuration based on the 4:1 time-division-multiplexing scheme. A mode-switch unit is provided to operate under control of the operation system to switch between the 3DS0
35 time-division-multiplexing scheme and the 4:1 time-division-multiplexing scheme. Because of such a configuration, this system can be connected to both

the switches of 3DS0 time-division-multiplexing scheme and the switches of the 4:1 time-division-multiplexing scheme.

Fig.2 is a block diagram of a relevant portion of the subscriber-system transmission apparatus 1 according to this embodiment for the purpose of explaining an EOC path during the 4:1 time-division-multiplexing mode.

As show in Fig.2, the subscriber-system transmission apparatus 1 includes a common shell 11 and narrow band shells 12. The common shell 11 includes a multiplexing/demultiplexing card 13, a cross-connect card 14, a SW-interface unit 15, and an EOC control card 16. The multiplexing/demultiplexing card 13 is comprised of a HC1A/HO10 unit, a TS1A unit, MC10 unit, etc. The cross-connect card 14 is comprised of a TS1C unit or the like, and the SW-interface unit 15 includes an EP1C unit or the like. The EOC control card 16 includes an EM1C unit or the like.

The narrow band shells 12 are provided as many as 10 units in parallel, and are connected to the cross-connect card 14 of the common shell 11. Each narrow band shell 12 includes a multiplexing/demultiplexing card 17 and 48 ISDN channel cards 18.

The multiplexing/demultiplexing card 13 of the common shell 11 is connected to the optical-fiber transmission lines via various interfaces such as OC3/OC12, OC3/D3/STS1, or DS1. Main signals 2B+D demultiplexed by the multiplexing/demultiplexing card 13 are supplied to the cross-connect card 14 during a period when the 4:1 time-division-multiplexing scheme is selected. In an opposite direction, the main signal 2B+D multiplexed by the cross-connect card 14 are supplied to the multiplexing/demultiplexing card 13.

An EOC signal demultiplexed by the multiplexing/demultiplexing card 13 is supplied to the cross-connect card 14 as an internal EOC after passing through the SW-interface unit 15 and the EOC control card 16. In the opposite direction, the internal EOC multiplexed by the cross-connect card 14 is supplied to the multiplexing/demultiplexing card 13 via the EOC control card 16 and the SW-interface unit 15.

The narrow band shells 12 attend to EOC/eoc conversion processing and EOC/I-bit conversion processing, and supply or receive the 2B+D and M channels at the U-point interface.

In Fig.2 showing the EOC path during the 4:1 time-division-multiplexing mode, signals transmitted to or received from OC3/OC12 are exchanged with the cross-connect card 14 via the multiplexing/demultiplexing card 13. On the other hand, the EOC (e.g., eoc bit + I bit) during the 4:1 time-division-multiplexing mode is exchanged between the multiplexing/demultiplexing card 13 and the narrow band shells 12 via the SW-interface unit 15 and the EOC control card 16 where SW-interface unit 15 provides necessary interface, and the EOC control card 16 attends to EOC control.

As shown in Fig.1, the switch system employing the subscriber-system transmission apparatus 1 does not require the related-art center-station (COT) transmission device 5 when it is connected to the TR303-type digital switches 2A through 2C. That is, the subscriber-system transmission apparatus 1 is connected to the TR303-type digital switches 2A through 2C via interface such as DS1. Since interface specifications (e.g., ISDN alarm detection) differ from vendor to vendor who manufacture the TR303-type digital switches 2A through 2C, a method of notifying an ISDN alarm is

changed depending on the types of the TR303-type digital switches 2A through 2C.

To this end, the control console 10 connected to the subscriber-system transmission apparatus 1 is used for making settings to switch options SWOPT. These settings make it possible to perform ISDN-alarm notification that complies to each of the switches. In the subscriber-system transmission apparatus 1, the switch options SWOPT may define that the companies A and C correspond to SWOPT1 and that the company B correspond to SWOPT2. The control console 10 serving as a switch-option setting unit is used for setting appropriate data to the SW-interface unit 15, the EOC control card 16, and the ISDN channel cards 18, thereby complying to the requirements of the switch to be connected. Switch option SWOPT3 is not in use because there is no vendor corresponding to this option. However, operation is guaranteed based on software specifications prior to correction of problems, so that backward compatibility is secured so as not to cause malfunction in apparatuses having only the EM1C unit thereof updated.

Fig.3 is a block diagram showing details of a portion relevant to settings of switch options in the subscriber-system transmission apparatus 1. Fig.3 is used for explaining a method of controlling alarm when the subscriber-system transmission apparatus 1 is connected to all the switches.

In Fig.3, the TR303-type digital switch 2A is made by the manufacturer A, and is connected to the subscriber-system transmission apparatus 1 via DS1. The switch setting is SWOPT1. The TR303-type digital switch 2B is made by the manufacturer B, and is connected to the subscriber-system transmission apparatus 1 via OC3. The switch setting is SWOPT2. The TR303-type digital switch 2C is a product of the

manufacturer C, and is connected to the subscriber-system transmission apparatus 1 via OC12. The switch setting is SWOPT1.

The SW-interface unit 15 of the subscriber-system transmission apparatus 1 includes three SW-interface units 151 through 153 corresponding to the respective TR303-type digital switches. The SW-interface units 151 through 153 can be set to the switch option SWOPT1, SWOPT2, or SWOPT3 by using the control console (SWOPT setting unit) 10. In this example, the SW-interface units 151 and 153 respectively connected to the TR303-type digital switches 2A and 2C are set to the switch setting (switch option) SWOPT1, and the SW-interface unit 152 connected to the TR303-type digital switch 2B is set to the switch option SWOPT2.

The SW-interface units 151 through 153 attend to conversion resembling language conversion, as will be described later, which corresponds to specifications of each of the TR303-type digital switches 2A through 2C.

The EOC control card 16 includes three EOC-control units 161 through 163, which correspond to the SW-interface units 151 through 153 of the SW-interface unit 15, respectively. The EOC-control units 161 through 163 are set to the switch option SWOPT1, SWOPT2, or SWOPT3 to conform to the switch-option settings of the SW-interface units 151 through 153 set by the control console 10. In the example shown in Fig.3, the EOC-control unit 161 has the switch option thereof set to SWOPT1 in conformity with the switch option setting of the SW-interface unit 151, and controls the EOC supplied from the SW-interface unit 151 via an EOC-termination unit 164. Further, the EOC-control unit 161 exchanges the internal EOC with the ISDN channel cards 18 via an internal-EOC-exchange unit 165.

The EOC-control units 161 through 163 convert alarm formats to conform to the specifications of the TR303-type digital switches 2A through 2C, which will be described later.

5 The cross-connect card 14 is provided between the EOC control card 16 and the ISDN channel cards 18, and attends to cross-connect processing. Under the remote control of the control console 10, the cross-connect card 14 can switch between the 4:1
10 time-division-multiplexing scheme and the 3DS0 time-division-multiplexing scheme with respect to each subscriber, and can establish a cross-connect between a given subscriber and any given subscriber number of any given switch. Further, the cross-
15 connect card 14 has service statuses (e.g., used/unused statuses of the B1 and B2 channels) and provisioning (e.g., settings of 4:1 TDM and 3DS0 TDM) thereof set through remote controlling.

Each of the ISDN channel cards 18 has 2
20 channels, each of which is connected to a corresponding one of the subscriber terminals (TE) 7 via the NT1 apparatus 6. Each channel of each ISDN channel card 18 includes three alarm-control units 181 through 183, an internal-EOC-exchange unit 184,
25 and a U-point-termination unit 185. The alarm-control units 181 through 183 are set to the switch option SWOPT1, SWOPT2, or SWOPT3. The internal-EOC-exchange unit 184 is equipped with the function of EOC/eoc conversion and the function of EOC/I-bit
30 conversion.

Fig.4 is a block diagram showing a configuration of the U-point-termination unit 185.

The U-point-termination unit 185 includes a U-point-synchronization-deviation-detection unit
35 1851, a NT1-power-supply-disconnection-detection unit 1852, a T-point-synchronization-deviation-detection unit 1853, alarm-control-switching unit

1854. The U-point-synchronization-deviation-detection unit 1851 detects loss of synchronization when synchronization is lost at the U point serving as connection interface with the NT1 apparatus 6.

5 The NT1-power-supply-disconnection-detection unit 1852 detects disconnection of power supply to the NT1 apparatus 6. The T-point-synchronization-deviation-detection unit 1853 detects loss of synchronization when synchronization is lost at the
10 T point. The alarm-control-switching unit 1854 selectively connects to one of the alarm-control units 181 through 183.

The alarm-control-switching unit 1854 is almost permanently connected to one of the alarm-
15 control units 181 through 183. This connected one of the alarm-control units 181 through 183 has the switch option SWOPT thereof set to conform to a TR303-type digital switch that is employed by the network to which the user of the channel belongs.

20 In the example of Fig.3, the channel CH1 of the ISDN channel card 18 is used by a user who belongs to a service-provider network that employs the TR303-type digital switch 2A manufactured by the manufacturer A. In order to connect the channel CH1
25 to the TR303-type digital switch 2A, the control console 10 is used to make connection settings to the cross-connect card 14. After this connection is established, the channel CH1 is set by the EOC control card 16 such as to carry out alarm control
30 of the switch option SWOPT1.

Fig.5 through Fig.7 are tables showing ISDN-alarm-notification commands and values thereof that are transmitted in response to the switch option settings corresponding to each switch vendor.

35 Fig.5 shows a case in which the alarm condition indicates loss of synchronization at the U point. Fig.6 shows a case where the power supply to the NT1

is disconnected. Fig.7 shows a case in which synchronization is lost at the T point.

With respect to the switch vendors A and C, a notification command that corresponds to the switch option SWOPT of 1 is used. With respect to the switch vendor B, a notification command that corresponds to the switch option SWOPT of 2 is used. Since the switch option SWOPT of 3 does not correspond to any vendor, it is not currently used. However, operation is guaranteed based on software specifications prior to correction of problems, so that backward compatibility is secured so as not to cause malfunction in apparatuses having only the EM1C unit thereof updated. What is shown in the figure is an EOP report that the subscriber-system transmission apparatus 1 transmits to the switch 2. LTOH represents m bits directed downstream at the U point, and NTOH represents m bits directed upstream at the U point.

In the case of loss of synchronization at the point U as shown in Fig.5, the Alarm Status Change Report is transmitted if the switch setting is SWOPT1 corresponding to the vendor A. In this case,

LTOH = '0111 1111 111' b, and
NTOH = '0000 0000 000' b.

If the switch setting is SWOPT2 corresponding to the vendor B, the Alarm Status Change Report and the NT1 Overhead Change Report are transmitted. In this case,

LTOH = '0111 1111 111' b, and
NTOH = '000x x101 111' b,

where "x" is the same value as one observed before loss of synchronization at the U point. If the switch setting is a default setting SWOPT3 corresponding to no vendor, the Alarm Status Change Report is transmitted. In this case,

LTOH = '1111 1111 111' b, and

NTOH = value received from the NT1 apparatus.

In this manner, the U-point-synchronization-deviation-detection unit detects

- 5 loss of synchronization at the U point, and notifies the switch of the alarm status. In so doing, only the Alarm Status Change Report should be sent to the switch if the switch is a product of the vendor A or C corresponding to the switch option SWOPT1.
- 10 Further, the act bit of LTOH should be set to 0, and all bits of NTOH should be set to 0. If the switch is a product of the vendor C corresponding to the switch option SWOPT2, both the Alarm Status Change Report and the NT1 Overhead Change Report should be sent.
- 15 In this case, the act bit of LTOH should be set to 0. Further, the act bit, the ps1 bit, the ps2 bit, and the sai bit of NTOH should be set to 0.

In the case of disconnection of power supply to the NT 1 as shown in Fig.6, the Alarm Status Change Report is transmitted if the switch setting is SWOPT1 corresponding to the vendor A. In this case,

LTOH = '0111 1111 111' b, and

NTOH = '0000 0000 000' b.

- 25 If the switch setting is SWOPT2 corresponding to the vendor B, the Alarm Status Change Report and the NT1 Overhead Change Report are transmitted. In this case,

LTOH = '0111 1111 111' b, and

- 30 NTOH = '000x x101 111' b,

where "x" is the same value as one observed before disconnection of power supply to the NT1. If the switch setting is a default setting SWOPT3 corresponding to no vendor, the Alarm Status Change

- 35 Report is transmitted. In this case,

LTOH = '1111 1111 111' b, and

NTOH = value received from the NT1 apparatus.

In this manner, the status of disconnection of power supply to the NT1 is the same as the status of loss of synchronization at the U point, resulting in transmission of the same
5 messages.

In the case of loss of synchronization at the T point as shown in Fig.7, the NT1 Overhead Change Report is transmitted if the switch setting is SWOPT1 corresponding to the vendor A. In this
10 case,

LTOH = '1111 1111 111' b, and

NTOH = '0xxx xxxx xxx' b,

where "x" is the same value as one observed before loss of synchronization at the T point. If the
15 switch setting is SWOPT2 corresponding to the vendor B, the NT1 Overhead Change Report are transmitted. In this case,

LTOH = '1111 1111 111' b, and

NTOH = '0xxx xx0x xxx' b,

20 where "x" is the same value as one observed before loss of synchronization at the T point. If the switch setting is a default setting SWOPT3 corresponding to no vendor, the NT1 Overhead Change Report is transmitted. In this case,

25 LTOH = '1111 1111 111' b, and

NTOH = value received from the NT1 apparatus.

In this manner, the T-point-synchronization-deviation-detection unit detects loss of synchronization at the T point, and notifies
30 the switch of the alarm status. The switch corresponding to the switch setting SWOPT1 detects loss of synchronization at the T point if the act bit of LTIH is 1 and the act bit of NTOH is 0. On the other hand, the switch corresponding to the
35 switch setting SWOPT2 detects loss of synchronization at the T point if the act bit of LTOH, the act bit of NTOH, and the sai bit are 1, 0,

0, respectively. Because of this, values as shown in Fig.7 are transmitted to let the switches properly detect loss of synchronization at the T point.

5 Fig.8 through Fig.11 are tables showing ISDN alarm notification commands and values thereof transmitted in response to switch settings of the EOC-control unit of the EOC control card 16. Fig.8 shows a case in which no ISDN channel card is in a
10 card slot. Fig.9 shows a case in which synchronization is lost at the U point. Fig.10 demonstrates a case where the power supply to the NT1 is disconnected. Fig.11 exhibits a case in which synchronization is lost at the T point.

15 When no ISDN channel card is in a card slot as shown in Fig.8, for example, only the M Event Report for ISDN-line-termination purposes should be transmitted if the switch setting is SWOPT1. If the switch setting is SWOPT2, however,
20 the M Event Report for ISDN-framing-path-termination-change purposes in the Overhead Bit Report should be transmitted in addition to the M Event Report for ISDN-line-termination purposes. The M Event Report for ISDN-framing-path-
25 termination-change purposes in the Overhead Bit Report should include data of LTOH and NTOH as shown in Fig.8.

 Fig.12 through Fig.14 are tables showing standards of ISDN alarm messages that are
30 transmitted in response to switch settings of the SW-interface unit of the SW-interface unit 15. Fig.12 shows ISDN alarm messages where the switch option is SWOPT1 corresponding to the vendor A. Fig.13 illustrates ISDN alarm messages where the
35 switch option is SWOPT2 corresponding to the vendor B. Fig.14 exhibits ISDN alarm messages where the switch option is set to a default value SWOPT3

corresponding to no existing vendor.

The subscriber-system transmission apparatus 1 operates as follows based on the mechanism as described above. In the following, it
5 is assumed that the subscriber terminal 7 covered by the channel CH1 of the ISDN channel cards 18 belongs to the service-provider network employing the TR303-type digital switch 2A of the vendor A, and that the subscriber terminal 7 covered by the channel CH2
10 belongs to the service-provider network employing the TR303-type digital switch 2B of the vendor B. As a consequence, the alarm-control-switching unit 1854 of the U-point-termination unit 185 for the channel CH1 is controlled so as to select the alarm-control unit 181 that corresponds to the switch
15 setting SWOPT1 of the vendor-A switch. Further, the alarm-control-switching unit 1854 of the U-point-termination unit 185 for the channel CH2 is controlled so as to select the alarm-control unit
20 182 that corresponds to the switch setting SWOPT2 of the vendor-B switch.

When the ISDN channel card 18 is taken out of the slot, for example, the EOC-control units 161 and 162 of the EOC control card 16 transmits alarm
25 messages to the TR303-type digital switches 2A and 2B, respectively, thereby notifying the inoperative statuses of the channels CH1 and CH2.

When synchronization is lost at the U point of the channel CH1 in the ISDN channel card 18,
30 for example, the U-point-termination unit 185 of the channel CH1 detects loss of synchronization at the U point. In response, the alarm-control unit 181 transmits an alarm-notification command that conforms to the switch option SWOPT1, and this
35 command is supplied to the TR303-type digital switch 2A from the internal-EOC-exchange unit 184 via the cross-connect card 14, the EOC control card 16, and

the SW-interface unit 15. This TR303-type digital switch 2A corresponds to the switch option SWOPT1. When synchronization is lost at the U point of the channel CH2, for example, the U-point-termination unit 185 of the channel CH2 detects loss of synchronization at the U point. In response, the alarm-control unit 182 transmits an alarm-notification command that conforms to the switch option SWOPT2, and this command is supplied to the TR303-type digital switch 2B from the internal-EOC-exchange unit 184 via the cross-connect card 14, the EOC control card 16, and the SW-interface unit 15. This TR303-type digital switch 2B corresponds to the switch option SWOPT2.

When synchronization is lost at the T point of the channel CH1 in the ISDN channel cards 18, the NT1 apparatus 6 connected to the channel CH1 sends a m-bit message indicative of loss of T-point synchronization to the channel CH1 of the ISDN channel cards 18 by passing the message through the U point. The alarm-control unit 181 then uses an alarm-notification command to transmit the EOC where the alarm-notification command conforms to the requirements of the vendor A.

In the following, operation of the U-point-termination unit 185 will be described in detail with reference to Fig.4. As was previously described, the U-point-termination unit 185 includes the U-point-synchronization-deviation-detection unit 1851, the NT1-power-supply-disconnection-detection unit 1852, and the T-point-synchronization-deviation-detection unit 1853. It should be noted here that the number of m bits used for reporting loss of synchronization at the T point varies depending on the types of NT1 apparatuses.

Some notify by use of the act bit that is 0, and others notify by use of the sai bit that is 0.

There are still some others that notify by use of the act bit and sai bit that are both zero. In order to detect loss of T-point synchronization with respect to any variation of these, the T-point-synchronization-deviation-detection unit 1853 of the U-point-termination unit 185 detects loss of T-point synchronization by checking if either one of the act bit and the sai bit is 0. When the m-bit message is supplied to the switch without any processing thereof, the switch cannot properly detect the loss of T-point synchronization. Because of this reason, the alarm-control unit 181 attends to conversion into LTOH and NTOH values that conform to the requirements of the vendor-A switch. This ensures that any type of a switch can be properly notified of loss of T-point synchronization regardless of the type of the NT1 that is connected to the ISDN channel card.

In the description provided above, the switches connected to the subscriber-system transmission apparatus 1 have been referred to as the TR303-type digital switches. If the switches of a network-service provider to which subscriber terminals belong are TR08-type digital switches, then, connection is established by using the TR08-type-switch mode. By the same token, if analog switches are used, connection is established by using the analog-switch mode.

For connection during the TR08-type-switch mode, none of the SW-interface unit 15 and the EOC control card 16 of the subscriber-system transmission apparatus 1 are used. Signals from the TR08-type digital switch are provided from the multiplexing/demultiplexing card 13 to the cross-connect card 14, which has switched to the 3DS0 time-division-multiplexing scheme. The alarm-control unit of the ISDN channel card 18 in this

case is comprised of only one type of alarm-control unit that conforms to the specifications of the TR08-type digital switch.

For connection during the analog-switch mode, the NT1 apparatus 6 of the subscriber terminal 7 is connected via the U-point-termination unit 185 of the ISDN channel card 18 directly to the cross-connect card 14, which has switched to the 3DS0 time-division-multiplexing scheme. This connection is established without having the alarm-control units 181 through 183 or the internal-EOC-exchange unit 184 as intervening units. Further, the connection is extended from the cross-connect card 14 to the center-station-system transmission apparatus 5 via an analog-switch multiplexing/demultiplexing unit 19 and the optical-fiber transmission line.

As described above, according to the present invention, no special work such as exchange of modules is necessary when there is a need to connect with switches operating based on the 4:1 time-division-multiplexing scheme. A relatively simple configuration includes the EOC-interface unit, the 4:1 TDM-cross-connect unit, the EOC/eoc-&-EOC/I-bit-conversion unit, etc., which is all that is necessary to implement the ISDN service providing connections with digital switches based on 4:1 time-division-multiplexing scheme in addition to rendering of the 3DS0 time-division-multiplexing service.

Further, the same configuration as in the conventional art is used with regard to MUX/DMUX interface, U-point interface, line structures, etc., thereby making it possible to cope with switches of the 4:1 time-division-multiplexing scheme without requiring major changes that may affect existing services.

Further, the present invention is not limited to these embodiments, but various variations and modifications may be made without departing from the scope of the present invention.

5 The present application is based on Japanese priority application No. 2000-076034 filed on March 17, 2000, with the Japanese Patent Office, the entire contents of which are hereby incorporated by reference.

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
221